

# ST6100

## EIGHT ZONE INTRUDER ALARM PANEL



LY69-022-72

- 8 zones, 7 fully programmable
- Choose LCD or LED keypad option
- Unique Sleep Watch keypad option
- Full guard, part guard and Sleep Watch arming
- 50-event non-volatile memory
- Separate bell, speaker, strobe and 2 SAB outputs
- Programmable entry, exit and siren timers
- Built-in sounder
- Back-lit keypad

A professional alarm panel with 7 programmable zones and 1 dedicated 24 hour tamper zone. The ST6100 can be used with a 32 digit LCD keypad, an LED keypad and the unique Sleep Watch keypad. Up to 6 LCD or LED keypads can be used and the panel offers a 50 event memory with time and date (LCD keypad only).

### Product Specification

Keypad Options:	Onboard 15 key rubber keypad with personal alarm LCD (K6600), LED (K6550) and Sleep Watch (SL6600) options.
Programmable Timers:	Fully programmable entry, exit and Sleep Watch 1-255 seconds activation time
Outputs:	2 Auxiliary 13.5V dc 250mA Bell output 12V dc timed reset Speaker rated at 1ohm Strobe 12V continuous until reset
Electrical:	Mains supply 220-240V ac
Physical:	Dimensions (HxLxW) 260 x 220 x 85mm Weight 1.8Kg

